



NEMA Configurations

This chart shows only the male (plug) configurations.



Dimensions = mm

Plug	NEMA	Outlet	NEMA	ANSI	A	B	C	∅ D	E	F	G
9530-P	5-30P	5371	5-30R	C73.45	94.1	57.1	56.3	53.6	111.1	70.2	47.9
9630-P	6-30P	5372	6-30R	C73.52	94.1	57.1	56.3	53.6			
9730-P	7-30P	9730-A	7-30R	C73.64	94.1	57.1	56.3	53.6			
9332-P	10-30P	5207	10-30R	C73.24	94.1	57.1	56.3	53.6			
9432-P	14-30P	278	14-30R	C73.16	95.3	69.8	56.5	61.9			
8432-P	15-30P	8430-A	15-30R	C73.60	95.3	69.8	53.3	61.9			
8332-P	18-30P	8330-A	18-30R	C73.43	95.3	69.8	53.3	61.9			
9550-P	5-50P	5373	5-50R	C73.46	94.1	57.1	56.3	53.6			
9650-P	6-50P	5374	6-50R	C73.53	94.1	57.1	56.3	53.6			
9750-P	7-50P	9750-A	7-50R	C73.65	94.1	57.1	56.3	53.6			
9450-P	10-50P	5206	10-50R	C73.25	94.1	57.1	56.3	53.6			
9452-P	14-50P	279	14-50R	C73.17	95.3	69.8	56.5	61.9			
8452-P	15-50P	8450-A	15-50R	C73.61	95.3	69.8	53.3	61.9			
8352-P	18-50P	8350-A	18-50R	C73.48	95.3	69.8	53.3	61.9			
9462-P	14-60P	9460-A	14-60R	C73.18	95.3	69.8	53.3	61.9			
8462-P	15-60P	8460-A	15-60R	C73.62	95.3	69.8	53.3	61.9			
8362-P	18-60P	8360-A	18-60R	C73.27	95.3	69.8	53.3	61.9			

Plug dims.
all the same.

Steckermaße
alle gleich.