

MW 1000 1000 Watts Step-Down Voltage Converter

Applications

- Business Machines, Radio/TV, Tape Decks etc.

Country Specification

- Continental Europe (Germany, France/Belgium etc.)

Characteristics

Voltage Rating:

- Input: 220-240V a.c. 50Hz
- Output: 110-120V a.c. 50Hz

Product Description

- Input Method: Desktop
- Primary Fuse F10 Amp. (5x20)mm
- Plug SCHUKO (CEE 7/VII)
- Cord length 1.6m H03VV-F 3G0.75mm²
- Power ON/OFF switch
- Power-on pilot light
- Output Method: Two (2) USA Receptacles, NEMA 5-15R

Remarks

- Do not use on devices with individual power supplies or transformers !

Availability

- 1 Piece Package as indicated
- Small quantities available for stock items only, please check stock availability at: www.BiaGmbH.com



1000W Step-Down Voltage Converter				
Catalog No.	Color	Packing Size (ea)	Quantity	Wght/ea
MW 1000	Black	(34.5x19.5x23.0)cm	1	8320g

