

GROUP F



380/440/550/600 PRIMARY VOLTS — 115/230 SECONDARY VOLTS — 1Ø, 50/60 Hz

| CATALOG NO. | VA RATING | OUTPUT AMPS | APPROX. DIMENSIONS Inches (Cm.) | | | | | | APPROX. SHIP WEIGHT Lbs. (Kg.) | PRIMARY FUSE BLOCK Part No. | SECONDARY FUSE SIZE ^② 115 VOLTS |
|-------------|-----------|-------------|------------------------------------|----------------|----------------|----------------|----------------|--------------------------|-----------------------------------|--------------------------------|---|
| | | | A | B | C | D | E | F | | | |
| TA-2-54535 | 50 | 0.43 | 4.12 (10.5) | 3.75 (9.5) | 3.21 (8.2) | 3.13 (8.0) | 2.19 (5.6) | .22 x .50 (0.6 x 1.3) | 4 (1.8) | PL-112701 | ⁶ / ₁₀ amp |
| TA-2-54536 | 100 | 0.87 | 4.56 (11.6) | 3.75 (9.5) | 3.21 (8.2) | 3.13 (8.0) | 2.31 (5.9) | .22 x .50 (0.6 x 1.3) | 5 (2.3) | PL-112701 | 1 ¹ / ₄ amps |
| TA-2-54537 | 150 | 1.30 | 5.00 (12.7) | 3.75 (9.5) | 3.21 (8.2) | 3.13 (8.0) | 3.06 (7.8) | .22 x .50 (0.6 x 1.3) | 10 (4.5) | PL-112701 | 2 amps |
| TA-2-54538 | 250 | 2.17 | 5.49 (13.9) | 4.50 (11.4) | 3.84 (9.8) | 3.75 (9.5) | 3.50 (8.9) | .22 x .50 (0.6 x 1.3) | 11 (5.0) | PL-112702 | 3 ¹ / ₂ amps |
| TA-2-81197 | 350 | 3.04 | 6.03 (15.3) | 4.88 (12.4) | 4.15 (10.5) | 4.06 (10.3) | 4.38 (11.1) | .22 x .50 (0.6 x 1.3) | 17 (7.7) | PL-112703 | 5 amps |
| TA-2-54539 | 500 | 4.35 | 6.76 (17.1) | 4.88 (12.4) | 4.15 (10.5) | 4.06 (10.3) | 5.75 (14.6) | .22 x .50 (0.6 x 1.3) | 23 (10.4) | PL-112703 | 7 amps |
| TA-2-81240 | 750 | 6.52 | 7.19 (18.3) | 6.75 (17.1) | 5.72 (14.5) | 5.75 (14.6) | 3.69 (9.4) | .31 x .50 (0.8 x 1.3) | 25 (11.3) | PL-112705 | 10 amps |
| TA-2-81241 | 1000 | 8.70 | 7.77 (19.7) | 6.75 (17.1) | 5.72 (14.5) | 5.75 (14.6) | 4.44 (11.3) | .31 x .50 (0.8 x 1.3) | 30 (13.6) | PL-112705 | 12 amps |

GROUP G

240/416/480/600; 230/400/460/575; 220/380/440/550; 208/500 PRIMARY VOLTS 99/120/130; 95/115/125; 91/110/120; 85/100/110 SECONDARY VOLTS — 1Ø, 50/60 Hz

| CATALOG NO. | VA RATING | OUTPUT AMPS | APPROX. DIMENSIONS Inches (Cm.) | | | | | | APPROX. SHIP WEIGHT Lbs. (Kg.) | PRIMARY FUSE BLOCK Part No. | SECONDARY FUSE KIT ^① Part No. | SECONDARY FUSE SIZE 130 VOLTS |
|-------------|-----------|-------------|------------------------------------|-----------------|----------------|----------------|----------------|--------------------------|-----------------------------------|--------------------------------|---|-------------------------------------|
| | | | A | B | C | D | E | F | | | | |
| TA-2-32403 | 50 | 0.38 | 4.08 (10.4) | 3.75 (9.5) | 3.21 (8.2) | 3.13 (8.0) | 2.31 (5.9) | .22 x .50 (0.6 x 1.3) | 5 (2.3) | PL-112701 | PL-112600 | ⁶ / ₁₀ amp |
| TA-2-32404 | 150 | 1.15 | 4.75 (12.1) | 4.50 (11.4) | 3.84 (9.8) | 3.75 (9.5) | 3.05 (7.7) | .22 x .50 (0.6 x 1.3) | 10 (4.5) | PL-112702 | PL-112601 | 1 ⁶ / ₁₀ amps |
| TA-2-32405 | 250 | 1.92 | 5.58 (14.2) | 4.88 (12.4) | 4.15 (10.5) | 4.06 (10.3) | 4.06 (10.3) | .22 x .50 (0.6 x 1.3) | 16 (7.3) | PL-112703 | PL-112601 | 3 ² / ₁₀ amps |
| TA-2-32669 | 350 | 2.69 | 6.23 (15.8) | 4.88 (12.4) | 4.15 (10.5) | 4.06 (10.3) | 5.50 (14.0) | .22 x .50 (0.6 x 1.3) | 22 (10.0) | PL-112703 | PL-112601 | 4 amps |
| TA-2-32406 | 500 | 3.85 | 6.40 (16.3) | 6.75 (17.1) | 5.72 (14.5) | 5.75 (14.6) | 3.69 (9.4) | .22 x .50 (0.6 x 1.3) | 23 (10.4) | PL-112705 | PL-112601 | 6 ¹ / ₄ amps |
| TA-2-54523 | 750 | 5.77 | 7.08 (18.0) | 6.75 (17.1) | 5.72 (14.5) | 5.75 (14.6) | 4.13 (10.5) | .31 x .50 (0.8 x 1.3) | 29 (13.2) | PL-112705 | PL-112601 | 9 amps |
| TA-2-54524 | 1000 | 7.69 | 8.56 (21.7) | 6.75 (17.1) | 5.72 (14.5) | 5.75 (14.6) | 4.88 (12.4) | .31 x .50 (0.8 x 1.3) | 35 (15.9) | PL-112705 | PL-112601 | 12 amps |
| TA-2-54525 | 1500 | 11.54 | 6.75 (17.1) | 7.50 (19.1) | 7.66 (19.5) | 6.50 (16.5) | 5.42 (13.8) | .41 x .81 (1.0 x 2.1) | 55 (24.9) | PL-112706 | PL-112601 | 20 amps |
| TA-2-81202 | 2000 | 15.39 | 7.45 (18.9) | 7.50 (19.1) | 7.66 (19.5) | 6.50 (16.5) | 6.12 (15.5) | .41 x .81 (1.0 x 2.1) | 55 (24.9) | PL-112706 | PL-112601 | 25 amps |
| TA-2-81203 | 3000 | 23.08 | 7.02 (17.8) | 11.92 (30.3) | 8.83 (22.4) | 6.75 (17.1) | 5.75 (14.6) | .41 x .81 (1.0 x 2.1) | 70 (31.8) | PL-112707 | — | — |
| TA-2-81205 | 5000 | 38.46 | 7.52 (19.1) | 11.92 (30.3) | 9.49 (24.1) | 6.75 (17.1) | 6.25 (15.9) | .41 x .81 (1.0 x 2.1) | 110 (49.9) | PL-112707 | — | — |

CONNECTION DETAILS FOR GROUP G

| Connect To Line For Respective Voltage | | | | | Output Volts | |
|--|-------|-------|-------|-------|--------------|-------|
| H1-H2 | H1-H3 | H1-H4 | H1-H5 | X1-X2 | X1-X3 | X1-X4 |
| 208 | — | — | 500 | 85 | 100 | 110 |
| 220 | 380 | 440 | 550 | 91 | 110 | 120 |
| 230 | 400 | 460 | 575 | 95 | 115 | 125 |
| 240 | 416 | 480 | 600 | 99 | 120 | 130 |

① Secondary Fuse Kit PL-112603 may be substituted for PL-112600 thru PL-112602 when Primary Fuse Kit is used. See page 75.

② Secondary fuse kit application for 115V only.