


Plastic Boxes Old Work Boxes, Shallow Boxes & DataCom Rings


03PS0003

Catalog Number	Cu. In. Vol.	Description	Dimensions (inches)			Wire, Fill (AWG)	Qty. Per Carton
			L	W	D		
Old Work Switch & Outlet Boxes with Quick/Click							
S1-18-W	18.0	Single gang. Swing-bracket for mounting adjusts from 1/4" down to 1/8". 2 Auto/Clamps® each end.	3 ²³ / ₃₂	2 ¹ / ₄	3 ³ / ₃₂	9 No. 14 8 No. 12 7 No. 10	100
S2-32-W	32.0	Two gang. Swing-bracket for mounting adjusts from 1/4" down to 1/8". 4 Auto/Clamps each end.	3 ²³ / ₃₂	4 ¹ / ₁₆	3 ³ / ₃₂	16 No. 14 14 No. 12 12 No. 10	50
S3-52-W	52.0	Three gang. Swing-bracket for mounting adjusts from 1/4" down to 1/8". 6 Auto/Clamps each end.	3 ²³ / ₃₂	5 ⁵ / ₁₆	3 ³ / ₃₂	26 No. 14 23 No. 12 20 No. 10	10
Deep Old Work Switch & Outlet Boxes with Quick/Click							
S1-22-W	22.0	Single gang deep. Swing-bracket for mounting adjusts from 1/4" down to 1/8". 2 Auto/Clamps each end.	3 ²³ / ₃₂	2 ⁵ / ₁₆	3 ¹ / ₂		50
Shallow Switch & Outlet Boxes for use in limited depth applications							
P1-08-W	8.0	Single gang. Old work flange box for retrofit applications.	3 ³ / ₄	2 ⁵ / ₁₆	1 ¹ / ₈		20
P1-08-N	8.0	Single gang. With vertical side bracket for new construction applications.	3 ³ / ₄	2 ⁵ / ₁₆	1 ¹ / ₈		20
DataCom Rings for class 2 low-voltage applications							
P1-00-WD	8.0	Gangable low-voltage ring. Swing bracket for mounting, adjusts from 1/4" down to 1/8", for old work, stand alone applications.	3 ²³ / ₃₂	2	N/A		15
P1-00-ND	8.0	Single gang. With vertical side bracket for new construction, with wire retaining fingers.	3 ³ / ₄	2 ³ / ₈	1 ¹ / ₄		15


All boxes are UL listed.




S1-18-W




S2-32-W




S3-52-W




P1-00-WD




P1-00-ND



P1-08-N



P1-08-W



S1-22-W

All devices listed on this page conform to NEMA OS2.